

Finite Element Simulation of Love Wave Based SAW Delay Line Using COMSOL Multiphysics

S. Trivedi¹, H. B. Nemade²

¹Center for Nanotechnology, Indian Institute of Technology Guwahati, Guwahati, Assam, India

²Department of Electronics and Electrical Engineering, Indian Institute of Technology Guwahati, Guwahati, Assam, India

Abstract

INTRODUCTION: A Surface acoustic wave (SAW) device consists of metal interdigital electrodes (IDT) made over the piezoelectric substrate. Application of sinusoidal voltage to the IDT launches an elastic wave on the surface due to inverse piezoelectric effect [1, 2]. SAW can be a promising bio-sensing platform but the conventional Rayleigh wave based SAW devices have vertical particle displacements which leads to attenuation in liquid media [3]. To avoid this problem, SAW devices are required which generate in-plane shear-horizontal wave motion such as the Love wave (LW) devices [4]. A LW device consists of a waveguide layer coated over the substrate generating a leaky SAW [5, 6].

USE OF COMSOL MULTIPHYSICS: The 3D geometry used for simulation in COMSOL Multiphysics along with time response snapshots are shown in Figure 1. The desired orientation of 36° -YX Lithium Tantalate (LT) is obtained through rotated coordinate system. The device operates at $\lambda = 12 \mu\text{m}$. The input and output IDTs of electrode width $\lambda/4$ are made over the substrate. A $4.7 \mu\text{m}$ thick SiO₂ film is considered as wave guiding layer. Periodic boundary condition (PBC) with continuity is assumed along z axis which effectively makes the IDTs of infinite aperture [7]. A critically damped region of size $2*\lambda$ is made near the boundaries so that there are no reflections from the edges. A sinusoidal voltage of $V_{in} = 5\sin(2\pi ft)$ V, with $f = 325 \text{ MHz}$ is applied to the input IDT. The simulation is run for 50 ns with a time step of 0.01 ns. Thin PMMA layer is put over the delay region to simulate mass loading. Time response simulation in the MEMS model is performed to compute time delay and phase shift with respect to the plain surface and used to compute the phase mass sensitivity of the device [8]. The insertion loss (IL) of the device is obtained by taking the Fourier transform of the system's impulse response.

RESULTS: The in-plane horizontal displacements are much larger compared to vertical displacements which confirm the shear-horizontal wave nature of LW (Figure 2). The voltage at the output IDT starts to rise in about 15.5 ns which give a Love wave phase velocity of 3850 m/sec. The Love wave device offers a phase mass sensitivity of 88.03 m²/kg (Figure 3). The delay line gives insertion loss of -32.2 dB and loading the device with 200 nm thick PMMA layer generates an additional loss of about 0.25 dB (Figure. 4).

CONCLUSIONS: The paper has presented finite element simulation of Love wave based SAW delay line device comprising of 36° -YX LT substrate with SiO₂ guiding layer. Typically delay line simulation requires large geometry and memory usage but using PBC in COMSOL

Multiphysics aids to keep the geometry small. Time response simulation of LW delay line is performed to calculate output voltage, displacements, mass sensitivity and IL. The mass sensitivity value obtained is consistent with previously reported values [9, 10]. Love wave devices are very important for designing bio-sensors and simulations in COMSOL Multiphysics help to obtain the device characteristics prior to actual fabrication.

Reference

- [1] R. M. White and F. W. Voltmer, "Direct Piezoelectric Coupling To Surface Elastic Waves," *Appl. Phys. Lett.*, vol. 7, no. 12, p. 314, 1965.
- [2] C. Campbell, *Surface acoustic wave devices and their signal processing applications*. Academic press, 1989.
- [3] J. Sakong, Y. Roh, and H. Roh, "SAW Sensor System with Micro-Fluidic Channels to Detect DNA Molecules," 2006 IEEE Ultrason. Symp., pp. 548–551, 2006.
- [4] G. L. Harding, J. Du, P. R. Dencher, D. Barnett, and E. Howe, "Love wave acoustic immunosensor operating in liquid," *Sensors Actuators A Phys.*, vol. 61, no. 1–3, pp. 279–286, Jun. 1997.
- [5] S. J. Powell, David A and Kalantar-Zadeh, Kourosch and Wlodarski, Wojtek and Ippolito, "Layered surface acoustic wave chemical and Bio-Sensors," *Encycl. Sensors. California, USA Am. Sci. Publ. Stevenson Ranch*, vol. X, pp. 1–18, 2006.
- [6] G. McHale, M. I. Newton, F. Martin, E. Gizeli, and K. a. Melzak, "Resonant conditions for Love wave guiding layer thickness," *Appl. Phys. Lett.*, vol. 79, no. 21, p. 3542, 2001.
- [7] M. Hofer, N. Finger, G. Kovacs, J. Schöberl, S. Zaglmayr, U. Langer, and R. Lerch, "Finite-element simulation of wave propagation in periodic piezoelectric SAW structures," *IEEE Trans. Ultrason. Ferroelectr. Freq. Control*, vol. 53, no. 6, pp. 1192–1200, 2006.
- [8] M.-I. Rocha-Gaso, R. Fernandez-Diaz, a. Arnau-Vives, and C. March-Iborra, "Mass sensitivity evaluation of a Love wave sensor using the 3D Finite Element Method," 2010 IEEE Int. Freq. Control Symp., pp. 228–231, Jun. 2010.
- [9] J. W. Grate, S. J. Martin, and R. M. White, "Acoustic Wave Microsensors Part II," *Anal. Chem.*, vol. 65, no. 22, p. 987A–996A, 1993.
- [10] N. Barié, T. Wessa, M. Bruns, and M. Rapp, "Love waves in SiO₂ layers on STW-resonators based on LiTaO₃," *Talanta*, vol. 62, no. 1, pp. 71–79, Jan. 2004.

Figures used in the abstract




Figure 1: (a) Simulation Geometry of the device. (b) Snapshots of time response of LW delay line at (b) 4 ns (c) 8 ns (d) 12 ns and (e) 16 ns.




Figure 2: (a) Variation of input and output voltage with time. (b) Plot of normalized displacements u_x , u_y and u_z at the output IDT with time.




Figure 3: (a) Plot of output voltage versus time for the plain surface and 200 nm thick PMMA loaded surface. Inset shows the time delay between two waveforms. (b) Plot of normalized phase shift ($\Delta\phi/kD$) versus incremental mass per unit area (Δm). The slope of the straight line represents the phase mass sensitivity.




Figure 4: (a) Insertion loss of delay line. (b) Insertion loss due to PMMA mass loading.